

AiM Infotech

Sensore di pressione
0-100 bar/0-1450 PSI
Configurazione con Race
Studio 3

Versione 1.00



1

Introduzione

Quando il sensore di pressione 0-100 bar è collegato fisicamente ad un canale dello strumento è necessario caricarlo nella relativa configurazione col software di configurazione AiM. In questo datasheet esso verrà caricato nella configurazione dello strumento con **Race Studio 3**.

2

Configurazione con Race Studio 3

- con lo strumento acceso e collegato al PC lanciare il software e selezionare lo strumento cui il sensore viene collegato;
- selezionare la configurazione sulla quale si vuole impostare il sensore o crearne una nuova premendo il tasto "Nuova" e selezionare il layer "Canali" mostrato sotto;
- scegliere il canale su cui si vuole impostare il sensore (nell'esempio sotto il Canale 1) e cliccare sulla relativa cella della colonna "Sensore";

The screenshot shows the RaceStudio3 3.05.02 software interface. The 'Channels' tab is active, displaying a table with columns: ID, Name, Function, Sensor, Unit, Freq, and Parameters. The 'Channel01' row is selected, and a mouse cursor is pointing at the 'Generic 0-5 V' cell in the 'Sensor' column.

ID	<input checked="" type="checkbox"/>	Name	Function	Sensor	Unit	Freq	Parameters
RPM	<input checked="" type="checkbox"/>	RPM	RPM	RPM Sensor	rpm	20 Hz	max: 16000 ; factor: /1 ;
Spd1	<input type="checkbox"/>	Speed1	Vehicle Spd	Speed Sensor	km/h 0.1	20 Hz	wheel: 1600 ; pulses: 1 ;
Spd2	<input type="checkbox"/>	Speed2	Vehicle Spd	Speed Sensor	km/h 0.1	20 Hz	wheel: 1600 ; pulses: 1 ;
Spd3	<input type="checkbox"/>	Speed3	Vehicle Spd	Speed Sensor	km/h 0.1	20 Hz	wheel: 1600 ; pulses: 1 ;
Spd4	<input type="checkbox"/>	Speed4	Vehicle Spd	Speed Sensor	km/h 0.1	20 Hz	wheel: 1600 ; pulses: 1 ;
Ch01	<input type="checkbox"/>	Channel01	Voltage	Generic 0-5 V	mV	20 Hz	
Ch02	<input type="checkbox"/>	Channel02	Voltage	Generic 0-5 V	mV	20 Hz	
Ch03	<input type="checkbox"/>	Channel03	Voltage	Generic 0-5 V	mV	20 Hz	
Ch04	<input type="checkbox"/>	Channel04	Voltage	Generic 0-5 V	mV	20 Hz	

- apparirà un pannello di configurazione
- selezionare la funzione: "Pressione" ed il tipo di pressione prescelta (1) tra
 - Oil pressure (pressione olio)
 - Brake Pressure (pressione freni)
 - Wheel Brake Pressure (Pressione freno ruota)
 - Pressure (pressione generica – come nell'esempio)
- scegliere poi il sensore "AiM 0-100 bar (X05SNP31100R)" (2)
- premere "Save" (3)
- premere "Transmit" (4)

The screenshot shows the RaceStudio3 3.05.02 software interface. The main window displays a table of channels with columns for ID, Name, Function, Sensor, Unit, Freq, and Parameters. Channel01 is selected, and its settings are shown in a pop-up 'Channel Settings' dialog box. The dialog box has the following fields:

- Name: Channel01
- Function: Pressure (marked with 1)
- Sensor: AiM 0-100 bar (X05SNP31100R) (marked with 2)
- Sampling Frequency: 20 Hz
- Unit of Measure: bar
- Display Precision: 2 decimal places
- Buttons: Save (marked with 3) and Cancel

In the main window, the 'Transmit' button is marked with 4. The table below shows the channel settings for Channel01:

ID	Name	Function	Sensor	Unit	Freq	Parameters
RPM	<input checked="" type="checkbox"/> RPM	RPM	RPM Sensor	rpm	20 Hz	max: 16000 ; factor: /1 ;
Spd1	<input type="checkbox"/> Speed1	Vehicle Spd	Speed Sensor	km/h 0.1	20 Hz	wheel: 1600 ; pulses: 1 ;
Spd2	<input type="checkbox"/> Speed2	Vehicle Spd	Speed Sensor	km/h 0.1	20 Hz	wheel: 1600 ; pulses: 1 ;
Spd3	<input type="checkbox"/> Speed3	Vehicle Spd	Speed Sensor	km/h 0.1	20 Hz	wheel: 1600 ; pulses: 1 ;
Spd4	<input type="checkbox"/> Speed4	Vehicle Spd	Speed Sensor	km/h 0.1	20 Hz	wheel: 1600 ; pulses: 1 ;
Ch01	<input checked="" type="checkbox"/> Channel01	Voltage	Generic 0-5 V	mV	20 Hz	
Ch02	<input type="checkbox"/> Channel02	Voltage				
Ch03	<input type="checkbox"/> Channel03	Voltage				
Ch04	<input type="checkbox"/> Channel04	Voltage				
Ch05	<input type="checkbox"/> Channel05	Voltage				
Ch06	<input type="checkbox"/> Channel06	Voltage				
Ch07	<input type="checkbox"/> Channel07	Voltage				
Ch08	<input type="checkbox"/> Channel08	Voltage				
AccX	<input checked="" type="checkbox"/> AccelerometerX	Inline Acc				
AccY	<input checked="" type="checkbox"/> AccelerometerY	Lateral Acc				
AccZ	<input checked="" type="checkbox"/> AccelerometerZ	Vertical Acc				
GyrX	<input checked="" type="checkbox"/> GyroX	Roll Rate				
GyrY	<input checked="" type="checkbox"/> GyroY	Pitch Rate				
GyrZ	<input checked="" type="checkbox"/> GyroZ	Yaw Rate				
Spd	<input checked="" type="checkbox"/> GPS Speed	Vehicle Sp				
OdD	<input checked="" type="checkbox"/> Odometer	Odometer Total	AIM ODO	km 0.1	1 Hz	